

**Nodes Double Wall****KWL1012 1.0****VISUAL COMFORT & Co.**

## STUDIO COLLECTION

**GENERAL PRODUCT INFORMATION:**

These fixtures are intended to be installed utilizing NEC compliant junction boxes.


This product is safety listed for damp locations.

Incandescent lamps may be dimmed with a standard incandescent dimmer. LED lamps may be dimmed with a LED dimmer. Consult lamp manufacturer for additional information.

**CAUTION - RISK OF FIRE**

This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.

Use minimum 90°C supply conductors.



- 1** Secure the mounting plate to the junction box.
- 2** Connect the fixture ground wire to a suitable ground in accordance to local electrical codes.
- 3** Connect the white fixture wire to the neutral power line wire with a wire nut.
- 4** Connect the black fixture wire to the hot power line wire with a wire nut.
- 5** Mount the fixture onto the mounting plate and secure it in place with the fixture screws.
- 6** Screw the plates onto the sockets.
- 7** Install the lamps by pushing the lamp pins completely into the socket holes. Refer to the label on the socket for Max Wattage Information.
- 8** Install the shades by screwing them onto the sockets.

**SAVE THESE INSTRUCTIONS!**